



**ATA**

Makes Life Brighter

*Generators & Switchgear Solutions*

## ATA JD 250, 6068HFG55 / 6068HFU55 250 KVA

Generator Power (prime)		250 kVA prime/275 kVA stand-by				
Speed	Operation	Engine		Gen drive rating		
		kW (Gross)	Fan power	Gen. eff.	kVA	KWe
1500 rpm – 50 Hz	Prime power	228	12.5	93%	<b>250</b>	200
	Standby power	250	12.5	93%	<b>276</b>	221
1800 rpm – 60 Hz	Prime power	237	13.0	93%	<b>260</b>	208
	Standby power	260	13.0	93%	<b>287</b>	230

### General Data

Model (Bare/Power Unit)	6068HFG55 / 6068HFU55
Configuration	6 cylinders, in-line
Type	4-stroke
Displacement	6.8L
Bore and stroke	106 x 127 mm
Compression ratio	17.2 : 1
Rotation	Counterclockwise
Injection type	Electronic (HPCR)
Aspiration	Turbocharged (air to air cooled)
Starter	4.2 kW, 12V
Alternator	90 amp, 12V
Total lubricating capacity	32.5L
Service	Right hand side
Flywheel housing	SAE 3
Flywheel	11.5"
Cooling system	Water-cooled

### Power Unit data

Model (Power Unit)	6068HFU55
Cooling system design	Radiator/CAC
Radiator material	Copper
Coolant ratio	50% ethylene glycol - 50 %water
Engine coolant capacity	12.7L
Radiator coolant capacity	18.8L
Air filter	Dry type

### Fuel consumption (kg/h)

Frequency	Operation	25%	50%	75%	100%
1500 rpm – 50 Hz	Prime power	12.6	23.3	34.3	45.1
	Standby power	13.9	25.4	37.6	48.9
1800 rpm – 60 Hz	Prime power	13.1	23.8	34.7	45.1
	Standby power	14.2	25.6	37.5	49.9

### Dimensions

Type	Length (mm)	Width (mm)	Height (mm)	Fuel Tank ( L )	Weight (KG)
Open	2850	1000	1800	510	2200
Closed	4100	1300	1960	510	3275

UAE, Sharjah Airport, Saif Zone Warehouse 2 , Street 14

Mobile: +971529597871

E-mail: [Info@ataswg.com](mailto:Info@ataswg.com)

Website: [www.ataswg.com](http://www.ataswg.com)



# ATA

Makes Life Brighter

## Generators & Switchgear Solutions

### ALTERNATOR SPECIFICATIONS

**TAL046** - 230 to 365 kVA - 50 Hz / 288 to 438 kVA - 60 Hz

Insulation class	H	Excitation system 6-wire	SHUNT AREP+ / PMG
Winding pitch	2/3 (wind.6S - 6-wire / wind.6 - 12-wire)	AVR type	R150 R180
Number of wires	6 (12 option)	Excitation system 12-wire (option)	SHUNT AREP+ / PMG
Protection	IP 23	AVR type	R150 R180
Altitude	≤ 1000 m	Voltage regulation (**)	± 0.8 % ± 0.5 %
Overspeed	2250 R.P.M.	Total Harmonic Distortion THD (***) in no-load < 2.5 %	
Air flow 50 Hz	0.48 m³/s	Total Harmonic Distortion THD (***) in linear load < 5 %	
Air flow 60 Hz	0.58 m³/s	Waveform: NEMA = TIF (***)	< 50
AREP+/PMG Short-circuit current = 2.7 In: 5 seconds (*)		Waveform: I.E.C. = THF (***)	< 2%

### Control Panel

DSE4510
<b>Auto Start Control Module</b>
The DSE4510 is a compact Auto Start Control Module that has been developed to provide an outstanding range of features within a compact enclosure.
<b>OVERALL SIZE</b>
140 mm x 113 mm x 43 mm (5.5" x 4.4" x 1.5")
<b>PANEL CUTOUT SIZE</b>
118 mm x 92 mm (4.6" x 3.6")
<b>MAXIMUM PANEL THICKNESS</b>
8.0 mm (0.3")
<b>WEIGHT</b>
0.26kg
<b>PRODUCT VARIANTS</b>
4510-03 - 4510 Auto Start Control Module (Ct, Rtc)
4510-04 - 4510 Auto Start Control Module (Ct, Rtc, Htr)



### Optional configurations:

#### Engine accessories:

- ☐ Heavy-duty air filter
- ☐ Coolant heater
- ☐ Lubricant oil heater
- ☐ Fuel and Water Separator
- ☐ Lube oil rotary pump

#### Alternator And Accessories:

- ☐ Leroy somer/stamford
- ☐ Anti condensation heater
- ☐ PMG + AVR ◇ Double bearing
- ☐ alternator High voltage \_\_\_\_\_ kV
- ☐ RTDs for Bearing and winding

#### Cooling System:

- ☐ 55 degree Radiator
- ☐ Remote Radiator

#### Control System:

- ☐ AMF
- ☐ Parallel
- ☐ Practical type in low temperature environment
- ☐ Control Screen Heater
- ☐ Remote Annunciators
- ☐ Other (ComP, DEIF)

#### Circuit Breaker:

- ☐ 3/4 poles
- ☐ Fixed/handcart type
- ☐ Electric mechanism

#### Automatic Transfer Switch (ATS):

- ☐ ATS cabinet
- ☐ Contractor type ATS
- ☐ Motorized changeover type ATS

#### Start Battery:

- ☐ Nickel-cadmium battery
- ☐ Maintenance-free battery
- ☐ Battery charger and selector switch
- ☐ Charging current meter

#### External Fuel Tank:

- ☐ Single /double wall fuel tank (500-5000 L)
- ☐ Fuel Transfer pump

#### Exhaust Muffler:

- ☐ Residential grade
- ☐ Critical grade
- ☐ Hospital grade

#### Available for voltages :

- ☐ 400/230V, 480/277V, 380/220V, 440/254V, 416/240V, 220/127V, 208/120V

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971529597871

E-mail: [Info@ataswg.com](mailto:Info@ataswg.com)

Website: [www.ataswg.com](http://www.ataswg.com)



# ATA

Makes Life Brighter

## Generators & Switchgear Solutions

### Prime Rating:

Unlimited hours usage, with an average load factor of 80% over each 24 hours period. 10% overload is available for 1 hour in every 12 hours operation. 0 overload is permitted on standby power.

### Standby Rating:

Limited to 500 hours annual usage, with an average load factor of 80% of the published standby power rating over each 24 hours period. Up to 300 hours of annual usage may be run continuously. No over-load is permitted on standby power.

### Engine:

John Deere, including air filters, fuel filters, oil filter, starting motor and charging alternator etc.

### Warranty policy:

ATA products have a warranty for 12 months or 1000 hours whichever occurs first against any manufacturing defects

Wearing parts (filters), incorrect man-made operation, maintenance failures are excluded from the warranty policy

### Radiator:

50°C, fan protective shroud

### Fuel Tank:

Capacity of fuel tank is for 8– 10 hours running  
Built in fuel tank up to 800 kVA

### Circuit Breaker:

3 pole LS MCCB

### Alternator Type:

brushless AC alternator

### Control system alarms:

Over and Under Speed

Low and High Battery Volt. Start and Stop Failure Over Current Under / Over Generator Voltage

Low Oil Pressure  
Emergency stop High engine temperature



**STAMFORD**  
power generation

**DSE**



**LEROY  
SOMER**

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories without prior notice. All photos are representative and may not reflect exact mode.

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971529597871

E-mail: [Info@ataswg.com](mailto:Info@ataswg.com)

Website: [www.ataswg.com](http://www.ataswg.com)