



ATA

Makes Life Brighter

Generators & Switchgear Solutions

ATA Perkins - 1100 Series 1104C-44TAG2

Speed rpm	Type of operation	Typical generator output (Net)		Engine power			
				Gross		Net	
		kVA	kWe	kWm	hp	kWm	hp
1500	Primepower	101.4	81.4	93.6	125.5	90.1	120.8
	Standby (maximum)	111.9	89.6	103.0	138.0	99.5	133.4

Percent of prime power	Fuel consumption at 1500 rpm g/kWh	Fuel consumption at 1500 rpm l/hr
Standby (maximum)	205	24.9
Primepower	205	22.6
75%	207	17.1
50%	204	11.2

Engine package weights and dimensions		
Length	1259 mm	45.5 in
Width	721 mm	28.3 in
Height	966 mm	38.0 in
Weight (dry)	550 kg	1212 lb

Specification		
Number of cylinders	4 vertical in-line	
Bore and stroke	105 x 127 mm	4.3 x 5.0 in
Displacement	4.41 litres	269 in ³
Aspiration	Turbocharged, air to air charge cooled	
Cycle	4 stroke	
Combustion system	Direct injection	
Compression ratio	18.2:1	
Rotation	Anti-clockwise, viewed on flywheel	
Total lubricating capacity	8.0 litres	2.1 US gal
Cooling system	Water-cooled	
Total coolant capacity	12.6 litres	3.3 US gal

Dimensions

Type	Length (mm)	Width (mm)	Height (mm)	Fuel Tank (L)	Weight (KG)
Open	2400	775	1375	190	1200
Closed	2750	1100	1500	190	1810

UAE, Sharjah Airport, Saif Zone Warehouse 2 , Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

Technical information

Air inlet

- Mounted air filter

Fuel system

- Rotary type pump
- Ecoplus fuel filter

Lubrication system

- Wet cast iron sump with filler and dipstick
- Spin-on oil filter

Cooling system

- Thermostatically-controlled system with gear-driven circulation pump and belt-driven pusher fan
- Mounted radiator and piping incorporating air-to-air charge cooler

Electrical equipment

- 12 volt starter motor and 12 volt 65 amp alternator with DC output
- 12 volt shutdown solenoid energised to run
- Glow plug cold start aid

Flywheel and housing

- Flywheel to SAE J620 size 10/11½
- SAE 3 flywheel housing



UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

ALTERNATOR SPECIFICATIONS

TAL 044 - Three-phase 70 to 200 kVA- 50 Hz / 88 to 250 kVA- 60 Hz

Insulation class	H	Excitation system 6-wire	SHUNT AREP+ / PMG
Winding pitch	2/3 (wind.6S - 6-wire / wind.6 - 12-wire)	AVR type	R120 R180
Number of wires	6 (12 option)	Excitation system 12-wire (option)	SHUNT AREP+ / PMG
Protection	IP 23	AVR type	R120 R180
Altitude	≤ 1000 m	Voltage regulation (*)	± 1 % ± 0.5 %
Overspeed	2250 R.P.M.	Total Harmonic Distortion THD (**) in no-load < 2 %	
Air flow 50 Hz	0.29 m³/s	Total Harmonic Distortion THD (**) in linear load < 5 %	
Air flow 60 Hz	0.34 m³/s	Waveform: NEMA = TIF (**)	< 50
AREP+/PMG Short-circuit current = 2.7 In : 5 second		Waveform: I.E.C. = FHT (**)	< 2%

Control Panel

DSE4510

Auto Start Control Module

The DSE4510 is a compact Auto Start Control Module that has been developed to provide an outstanding range of features within a compact enclosure.

OVERALL SIZE

140 mm x 113 mm x 43 mm (5.5" x 4.4" x 1.5")

PANEL CUTOUT SIZE

118 mm x 92 mm (4.6" x 3.6")

MAXIMUM PANEL THICKNESS

8.0 mm (0.3")

WEIGHT

0.26kg

PRODUCT VARIANTS

4510-03 - 4510 Auto Start Control Module (Ct, Rtc)

4510-04 - 4510 Auto Start Control Module (Ct, Rtc, Htr)



Optional configurations:

Engine accessories:

- Heavy-duty air filter
- Coolant heater
- Lubricant oil heater
- Fuel and Water Separator
- Lube oil rotary pump

Alternator And Accessories:

- Leroy somer/stamford
- Anti condensation heater
- PMG + AVR ◇ Double bearing
- alternator High voltage _____kV
- RTDs for Bearing and winding

Cooling System:

- 55 degree Radiator
- Remote Radiator

Control System:

- AMF
- Parallel
- Practical type in low temperature environment
- Control Screen Heater
- Remote Annunciators
- Other (ComP, DEIF)

Circuit Breaker:

- 3/4 poles
- Fixed/handcart type
- Electric mechanism

Automatic Transfer Switch (ATS):

- ATS cabinet
- Contractor type ATS
- Motorized changeover type ATS

Start Battery:

- Nickel-cadmium battery
- Maintenance-free battery
- Battery charger and selector switch
- Charging current meter

External Fuel Tank:

- Single /double wall fuel tank (500-5000 L)
- Fuel Transfer pump

Exhaust Muffler:

- Residential grade
- Critical grade
- Hospital grade

Available for voltages :

- 400/230V, 480/277V, 380/220V, 440/254V, 416/240V, 220/127V, 208/120V

UAE, Sharjah Airport, Saif Zone Warehouse 2 , Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

Prime Rating:

Unlimited hours usage, with an average load factor of 80% over each 24 hours period. 10% overload is available for 1 hour in every 12 hours operation. 0 overload is permitted on standby power.

Standby Rating:

Limited to 500 hours annual usage, with an average load factor of 80% of the published standby power rating over each 24 hours period. Up to 300 hours of annual usage may be run continuously. No over-load is permitted on standby power.

Engine:

Perkins, including air filters, fuel filters, oil filter, starting motor and charging alternator etc.

Warranty policy:

ATA products have a warranty for 12 months or 1000 hours whichever occurs first against any manufacturing defects

Wearing parts (filters), incorrect man-made operation, maintenance failures are excluded from the warranty policy

Radiator:

50°C, fan protective shroud

Fuel Tank:

Capacity of fuel tank is for 8– 10 hours running
Built in fuel tank up to 800 kVA

Circuit Breaker:

3 pole LS MCCB

Alternator Type:

brushless AC alternator

Control system alarms:

Over and Under Speed
Low and High Battery Volt. Start and Stop Failure Over Current Under / Over Generator Voltage
Low Oil Pressure
Emergency stop High engine temperature



STAMFORD
power generation

DSE



LEROY SOMER

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories without prior notice. All photos are representative and may not reflect exact mode.

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com