



ATA

Makes Life Brighter

Generators & Switchgear Solutions

ATA Perkins, 1103A-33TG1, 45 KVA

Speed rpm	Type of operation	Typical generator output (Net)		Engine power			
				Gross		Net	
		kVA	kWe	kWm	hp	kWm	bhp
1500	Prime power	45.0	36.0	42.2	56.6	41.3	55.4
	Standby power	49.6	39.7	46.5	62.4	45.6	61.2

Percent of prime power	Fuel consumption at 1500 rpm	
	UK g/hr	l/hr
Standby power	2.57	11.70
Prime power	2.38	10.80
75%	1.81	8.23
50%	1.28	5.83
25%	0.77	3.49

Engine package weights and dimensions		
Length	1049 mm	41.3 in
Width	634 mm	24.9 in
Height	951 mm	37.4 in
Weight (dry)	420 kg	926 lb

Specification		
Number of cylinders	3 vertical in-line	
Bore and stroke	105 x 127 mm	4.1 in x 5 in
Displacement	3.3 litres	201 in ³
Aspiration	Turbocharged	
Cycle	4 stroke	
Combustion system	Direct injection	
Compression ratio	17.25:1	
Rotation	Anti-clockwise, viewed from flywheel	
Total lubricating capacity	7.9 litres	2.1 US gal
Cooling system	Water-cooled	
Total coolant capacity	10.2 litres	2.7 US gal

Dimensions

Type	Length (mm)	Width (mm)	Height (mm)	Fuel Tank (L)	Weight (KG)
Open	1950	775	1175	100	850
Closed	2260	1110	1500	100	1350

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

Technical information

Air inlet

Mounted air filter

Fuel system

Mechanically governed cassette type fuel injection pump Split element fuel filter

Lubrication system

Wet steel sump with filler and dipstick
Spin-on full-flow lub oil filter

Cooling system

Thermostatically-controlled system with belt driven coolant pump and pusher fan
Mounted radiator, piping and guards

Electrical equipment

12 volt starter motor and 12 volt 15 amp alternator with DC output Oil pressure and coolant temperature switches
12 volt shut-off solenoid energised to run
Glow plug cold start aid and heater/starter switch

Flywheel and housing

1500 rev/min
High inertia flywheel to SAE J620 Size 165.1 mm (6½ in) Heavy
Flywheel housing SAE 5 Long

Mountings

Front and rear engine mounting brackets



UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

ALTERNATOR SPECIFICATIONS

TAL 042 - Three-phase 25 to 60 kVA - 50 Hz / 31.5 to 75 kVA - 60 Hz

Insulation class	H	Excitation system 6-wire	SHUNT AREP
Winding pitch	2/3 (wind.6S - 6-wire / wind.6 - 12-wire)	AVR type	R120 R180
Number of wires	6-wire (12-wire option)	Excitation system 12-wire (option)	SHUNT AREP
Protection	IP 23	AVR type	R120 R180
Altitude	≤ 1000 m	Voltage regulation (*)	± 1 %
Overspeed	2250 R.P.M.	Total Harmonic Distortion THD (**) in no-load < 2 %	
Air flow 50 Hz (m³/s)	0.1	Total Harmonic Distortion THD (**) in linear load < 5 %	
Air flow 60 Hz (m³/s)	0.13	Waveform: NEMA = TIF (**)	< 50
AREP Short-circuit current = 2.7 In: 5 second		Waveform: I.E.C. = FHT (**)	< 2%

Control Panel

DSE4510

Auto Start Control Module

The DSE4510 is a compact Auto Start Control Module that has been developed to provide an outstanding range of features within a compact enclosure.

OVERALL SIZE

140 mm x 113 mm x 43 mm (5.5" x 4.4" x 1.5")

PANEL CUTOUT SIZE

118 mm x 92 mm (4.6" x 3.6")

MAXIMUM PANEL THICKNESS

8.0 mm (0.3")

WEIGHT

0.26kg

PRODUCT VARIANTS

4510-03 - 4510 Auto Start Control Module (Ct, Rtc)

4510-04 - 4510 Auto Start Control Module (Ct, Rtc, Htr)



Optional configurations:

Engine accessories:

- Heavy-duty air filter
- Coolant heater
- Lubricant oil heater
- Fuel and Water Separator
- Lube oil rotary pump

Alternator And Accessories:

- Leroy somer/stamford
- Anti condensation heater
- PMG + AVR ◊ Double bearing
- alternator High voltage _____kV
- RTDs for Bearing and winding

Cooling System:

- 55 degree Radiator
- Remote Radiator

Control System:

- AMF
- Parallel
- Practical type in low temperature environment
- Control Screen Heater
- Remote Annunciators
- Other (ComP, DEIF)

Circuit Breaker:

- 3/4 poles
- Fixed/handcart type
- Electric mechanism

Automatic Transfer Switch (ATS):

- ATS cabinet
- Contractor type ATS
- Motorized changeover type ATS

Start Battery:

- Nickel-cadmium battery
- Maintenance-free battery
- Battery charger and selector switch
- Charging current meter

External Fuel Tank:

- Single /double wall fuel tank (500-5000 L)
- Fuel Transfer pump

Exhaust Muffler:

- Residential grade
- Critical grade
- Hospital grade

Available for voltages :

- 400/230V, 480/277V, 380/220V, 440/254V, 416/240V, 220/127V, 208/120V

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

Prime Rating:

Unlimited hours usage, with an average load factor of 80% over each 24 hours period. 10% overload is available for 1 hour in every 12 hours operation. 0 overload is permitted on standby power.

Standby Rating:

Limited to 500 hours annual usage, with an average load factor of 80% of the published standby power rating over each 24 hours period. Up to 300 hours of annual usage may be run continuously. No over-load is permitted on standby power.

Engine:

Perkins, including air filters, fuel filters, oil filter, starting motor and charging alternator etc.

Warranty policy:

ATA products have a warranty for 12 months or 1000 hours whichever occurs first against any manufacturing defects

Wearing parts (filters), incorrect man-made operation, maintenance failures are excluded from the warranty policy

Radiator:

50°C, fan protective shroud

Fuel Tank:

Capacity of fuel tank is for 8– 10 hours running
Built in fuel tank up to 800 kVA

Circuit Breaker:

3 pole LS MCCB

Alternator Type:

brushless AC alternator

Control system alarms:

Over and Under Speed
Low and High Battery Volt. Start and Stop Failure Over Current Under / Over Generator Voltage
Low Oil Pressure
Emergency stop High engine temperature



STAMFORD
power generation

DSE



**LERoy
SOMER**

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories without prior notice. All photos are representative and may not reflect exact mode.

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com