



ATA

Makes Life Brighter

Generators & Switchgear Solutions

ATA Perkins, 1506A-E88TAG5, 300 KVA

Speed rpm	Type of operation	Typical generator output		Engine power (Net)	
		kVA	kWe	kWm	hp
1500	Prime power	300	240	267	358
	Standby power	330	264	293	393

Percent of prime power	Fuel consumption at 1500 rpm g/kWh	Fuel consumption at 1500 rpm l/hr
Standby power	202	73
Prime power	196	65
75%	195	48
50%	198	33

Engine package weights and dimensions		
Length (including air cleaner)	2032 mm	80 in
Width	1091 mm	43 in
Height	1320 mm	52 in
Weight (dry)	1183 kg	2608 lb

Specification		
Number of cylinders	6 vertical in-line	
Bore and stroke	112 x 149 mm	4.5 x 5.8 in
Displacement	8.8 litres	537 cubic in ³
Aspiration	Turbocharged aftercooled	
Cycle	4 stroke	
Combustion system	Direct injection	
Compression ratio	16.1:1	
Rotation	Anti-clockwise, viewed on flywheel	
Total lubricating capacity	41 litres	9.01 US gal
Cooling system	Liquid	

Dimensions

Type	Length (mm)	Width (mm)	Height (mm)	Fuel Tank (L)	Weight (KG)
Open	2980	1200	1850	670	2228
Closed	4322	1463	2210	670	3220

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

Technical information

Air inlet system

- Mounted air filter and turbocharger

Fuel system

- HEUI fuel system with full authority electronic control
- Electronic governing to ISO 8528-5 with stand-alone isochronous and load-sharing capabilities
- Fuel filter, fuel transfer pump, fuel priming pump
- Spin on primary, secondary and water filter separator

Lubrication system

- Wet full aluminium sump with filler and dipstick
- Full-flow spin-on filters
- Oil pump, gear driven

Cooling system

- Thermostatically controlled with belt driven, circulating pump and belt-drive fan
- Mounted belt driven pusher fan
- Radiator supplied loose with all guards and pipes
- Air-to-air charge cooler incorporated in radiator

Electrical equipment

- 24V starter motor and 24V, 45 amp alternator with DC output
- Electronic Control Module (ECM) mounted on engine with wiring looms and sensors

Flywheel and housing

- High inertia flywheel to SAE 1 J620 Size 355.6 mm (14 in)
- Aluminium SAE 1 flywheel housing

Mountings

- Front engine mounting bracket



UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

ALTERNATOR SPECIFICATIONS

TAL046 - 230to 365 kVA- 50Hz/288to 438 kVA- 60 Hz

Insulation class	H	Excitation system 6-wire	SHUNT AREP+ / PMG
Winding pitch	2/3 (wind.6S - 6-wire / wind.6 - 12-wire)	AVR type	R150 R180
Number of wires	6 (12 option)	Excitation system 12-wire (option)	SHUNT AREP+ / PMG
Protection	IP 23	AVR type	R150 R180
Altitude	≤ 1000 m	Voltage regulation (**)	± 0.8 % ± 0.5 %
Overspeed	2250 R.P.M.	Total Harmonic Distortion THD (***) in no-load < 2.5 %	
Air flow 50 Hz	0.48 m ³ /s	Total Harmonic Distortion THD (***) in linear load < 5 %	
Air flow 60 Hz	0.58 m ³ /s	Waveform: NEMA = TIF (***)	< 50
AREP+/PMG Short-circuit current = 2.7 In: 5 seconds (*)		Waveform: I.E.C. = THF (***)	< 2%

Control Panel

DSE7320 MKII
Auto Mains (Utility) Failure Control Module
The DSE7320 MKII is a powerful, new generation Auto Mains (Utility) Failure genset control module with a highly sophisticated level of new features and functions, presented in the usual DSE user-friendly format. Suitable for a wide variety of single, diesel or gas Gen-set applications.
OVERALL SIZE
245 mm x 184 mm x 51 mm (9.6" x 7.2" x 2.0")
PANEL CUTOUT SIZE
220 mm x 160 mm (8.7" x 6.3")
MAXIMUM PANEL THICKNESS
8.0 mm (0.3")
PRODUCT VARIANTS
7320-03 - 7320 MKII Auto Mains (Utility) Failure Control Module



Optional configurations:

Engine accessories:

- Heavy-duty air filter
- Coolant heater
- Lubricant oil heater
- Fuel and Water Separator
- Lube oil rotary pump

Alternator And Accessories:

- Leroy somer/stamford
- Anti condensation heater
- PMG + AVR ◇ Double bearing
- alternator High voltage,kV
- RTDs for Bearing and winding

Cooling System:

- 55 degree Radiator
- Remote Radiator

Control System:

- AMF
- Parallel
- Practical type in low temperature environment
- Control Screen Heater
- Remote Annunciators
- Other (ComP, DEIF)

Circuit Breaker:

- 3/4 poles
- Fixed/handcart type
- Electric mechanism

Automatic Transfer Switch (ATS):

- ATS cabinet
- Contractor type ATS
- Motorized changeover type ATS

Start Battery:

- Nickel-cadmium battery
- Maintenance-free battery
- Battery charger and selector switch
- Charging current meter

External Fuel Tank:

- Single /double wall fuel tank (500-5000 L)
- Fuel Transfer pump

Exhaust Muffler:

- Residential grade
- Critical grade
- Hospital grade

Available for voltages :

- 400/230V, 480/277V, 380/220V, 440/254V, 416/240V,220/127V, 208/120V

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com



ATA

Makes Life Brighter

Generators & Switchgear Solutions

Prime Rating:

Unlimited hours usage, with an average load factor of 80% over each 24 hours period. 10% overload is available for 1 hour in every 12 hours operation. 0 overload is permitted on standby power.

Standby Rating:

Limited to 500 hours annual usage, with an average load factor of 80% of the published standby power rating over each 24 hours period. Up to 300 hours of annual usage may be run continuously. No over-load is permitted on standby power.

Engine:

Perkins, including air filters, fuel filters, oil filter, starting motor and charging alternator etc.

Warranty policy:

ATA products have a warranty for 12 months or 1000 hours whichever occurs first against any manufacturing defects

Wearing parts (filters), incorrect man-made operation, maintenance failures are excluded from the warranty policy

Radiator:

50°C, fan protective shroud

Fuel Tank:

Capacity of fuel tank is for 8– 10 hours running
Built in fuel tank up to 800 kVA

Circuit Breaker:

3 pole LS MCCB

Alternator Type:

brushless AC alternator

Control system alarms:

Over and Under Speed
Low and High Battery Volt. Start and Stop Failure Over Current Under / Over Generator Voltage
Low Oil Pressure
Emergency stop High engine temperature



STAMFORD
power generation

DSE



**LEROY
SOMER**

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories without prior notice. All photos are representative and may not reflect exact mode.

UAE, Sharjah Airport, Saif Zone Warehouse 2, Street 14

Mobile: +971502296962

E-mail: Info@ataswg.com

Website: www.ataswg.com